



Trailing-edge phase dimmer for controlling with digital DSI or DALI signals. Suitable for incandescent lamps or electronic transformers with a connected

load of 50 to 500 W. With reversible protection for short-circuits and overtemperature.

Article no.	Description	Packaging unit
PRB-0.5-ENC-230	50..500 W Trailing-edge Phase Dimmer	10
Rated voltage	230 V; 50/60 Hz	
Load current	2.3 A max.	
Connected load	50..500 W (Rated voltage)	
Power loss (operation)	6 W max.	
Power loss (standby)	0,6 W max.	
Inputs	DSI/DALI	
Outputs	Dimmed phase (trailing-edge), 0-100% control range	
Ambient temperature	-20..45° C	
Weight	145 g	

